

(19) World Intellectual Property Organization
International Bureau



(43) International Publication Date
31 May 2001 (31.05.2001)


PCT

(10) International Publication Number
WO 01/39106 A1

- (51) International Patent Classification⁷: **G06K 9/00** Beaverton, OR 97008 (US). HANNIGAN, Brett, T.; 7400 SW Barnes Rd. #262, Portland, OR 97225 (US).
- (21) International Application Number: PCT/US00/32013
- (22) International Filing Date:
21 November 2000 (21.11.2000)
- (25) Filing Language: English
- (26) Publication Language: English
- (30) Priority Data:
09/444,770 22 November 1999 (22.11.1999) US
- (71) Applicant: DIGIMARC CORPORATION [US/US]; 19801 SW 72nd Avenue, Suite 250, Tualatin, OR 97062 (US).
- (74) Agent: GALBI, Elmer; 13314 Vermeer Drive, Lake Oswego, OR 97035 (US).
- (81) Designated States (*national*): AE, AG, AL, AM, AT, AU, AZ, BA, BB, BG, BR, BY, BZ, CA, CH, CN, CR, CU, CZ, DE, DK, DM, DZ, EE, ES, FI, GB, GD, GE, GH, GM, HR, HU, ID, IL, IN, IS, JP, KE, KG, KP, KR, KZ, LC, LK, LR, LS, LT, LU, LV, MA, MD, MG, MK, MN, MW, MX, MZ, NO, NZ, PL, PT, RO, RU, SD, SE, SG, SI, SK, SL, TJ, TM, TR, TT, TZ, UA, UG, UZ, VN, ZA, ZW.
- (81) Designated States (*regional*): ARIPO patent (GH, GM, KE, LS, MW, MZ, SD, SL, SZ, TZ, UG, ZW), Eurasian patent (AM, AZ, BY, KG, KZ, MD, RU, TJ, TM), European patent (AT, BE, CH, CY, DE, DK, ES, FI, FR, GB, GR, IE, IT, LU, MC, NL, PT, SE, TR), OAPI patent (BF, BJ, CF, CG, CI, CM, GA, GN, GW, ML, MR, NE, SN, TD, TG).

[Continued on next page]

(54) Title: ADJUSTING AN ELECTRONIC CAMERA TO ACQUIRE A WATERMARKED IMAGE



(57) Abstract: The present invention provides a mechanism for automatically setting the exposure time and gain of an electronic camera so that the acquired image has improved characteristics for the detection of a digital watermark. With the present invention the exposure time and gain of an electronic camera are set by first directing the camera at a test target with the camera's controls set to a default set of values (501). The system then calculates a histogram of the luminance values (503) of the pixels in the image. Next characteristic values from the histogram such as the peak value, the centroid value (505), the RMS value, the median value, etc. are calculated. One or more of the characteristic values of the histogram are then applied as an index or pointer to values of pre-established settings that are stored in a table. Values from the table are used to set the exposure time and/or gain (506) of the camera. In some embodiments, the variance of the luminance histogram is also measured and used to index data from the table.



Published:

- With international search report.
- Before the expiration of the time limit for amending the claims and to be republished in the event of receipt of amendments.

For two-letter codes and other abbreviations, refer to the "Guidance Notes on Codes and Abbreviations" appearing at the beginning of each regular issue of the PCT Gazette.

Adjusting an Electronic Camera to Acquire a Watermarked Image

Field of the Invention:

This invention relates to electronic cameras and more particularly to the control of electronic cameras.

Background of the Invention:

Electronic cameras are commercially available and in widespread use. The basic technology used in electronic cameras is well developed. Electronic cameras generally include CCD or CMOS light sensing elements. The exposure time of the light sensing elements and the gain of the readout circuitry can be set to control the quality of the images which are acquired by the camera.

Some electronic cameras have a built in exposure meter that detects the amount of light reaching the camera. The appropriate exposure time and gain of the sensing elements is then automatically set at values determined by the signal generated by the exposure meter.

Some electronic video cameras which are designed for integration into a personal computers provide the user with a menu such as that shown in Figure 1 which can be used to set various parameters to control the operation of the camera. A user typically sets the various parameters so that the camera will produce an image that is visually appealing to a human observer. A program in the computer adjusts the actual settings in the camera in a direction which attempts to have the images meet the specifications set by the user. This type of adjustment may take place over several sequential frames. Furthermore as ambient conditions change, the actual exposure time and gain of the sensing elements is varied between frames in an effort to meet the specifications set by the user.

Electronic cameras can be used as part of systems such as that shown in copending applications 09/314,648, 09/343,104, 60/158,015, and 60/163,332. The systems shown in the referenced copending applications are designed to detect a digital watermark in an image acquired by a video camera. In such systems after a video camera is used to acquire an image, the acquired image is digitally processed to detect a digital watermark

1 that is contained in the image. It has been found that the optimal settings for a camera
2 used in such systems is not necessarily the optimal settings that are established to
3 provide a pleasing image to a human viewer.

4
5 The type of parameters that can be established using a menu such as that shown in
6 Figure 1 do not always produce optimal conditions for detecting a digital watermark in an
7 acquired image.

8
9 **Summary of the present Invention:**

10 The present invention provides a mechanism for automatically setting the exposure time
11 and gain of an electronic camera so that the acquired image has improved characteristics
12 for the detection of a digital watermark. With the present invention the exposure time and
13 gain of an electronic camera are set by first directing the camera at an image with the
14 camera's controls set to a set of default or initial values. The system then calculates and
15 stores data which represents a histogram of the luminance values of the pixels in the
16 acquired image. Next characteristic values from the histogram data such as the peak
17 value, the centroid value, the RMS value, the median value, etc., are calculated. One or
18 more of the characteristic values of the histogram data are then applied as an index or
19 pointer to values of pre-established settings that are stored in a table. Values from the
20 table are used to set the exposure time and/or gain of the camera. In some
21 embodiments, the variance of the luminance histogram data is also measured and used to
22 index data from the table. In some embodiments, a test target is used to acquire an initial
23 image. In other embodiments, the initial image is made by pointing the camera at the
24 image which contains the watermark data.

25
26 **Detailed Description of the Figures:**

27 Figure 1 illustrates the screen presented to a user to enable the user to set the values that
28 control a camera.

29
30 Figure 2 is an overall diagram of a first embodiment of the present invention.

31
32 Figure 3 is a diagram that illustrates a luminance histogram.

33

Figure 4 is a diagram illustrating a table which stores values for exposure time for a camera's shutter.

Figure 5 is a flow diagram of the control program executed by the computer embedded in the camera.

Figure 6 is a flow diagram of an alternative embodiment.

Detailed Description of Embodiments of the invention:

The overall system shown in Figure 2 includes a conventional digital camera 21 and a conventional control computer 22. As is conventional the camera 21 includes a CCD detector 23 and a lens 24 which focuses an image on the CCD detector. The CCD detector 23 has a gain control line 23a and an exposure control line 23b. The control computer 22 controls the values on the lines 23a and 23b. While for convenience of illustration and explanation the camera 21 is shown in Figure 2 as an individual unit separated from control computer 22, it should be understood that in many commercially available systems the camera 21 is mounted within (or attached to) the computer 22 and lines 23a and 23b represent logical control lines rather than physical wires.

As is conventional the computer 22 includes memory 22a and programming 22b. For convenience and clarity of illustration and explanation these are illustrated as separate boxes in Figure 2. The other conventional parts of the camera 21 and the computer 22 are not illustrated in Figure 2 and not discussed herein since they are not particularly relevant to an explanation of the invention.

In the first preferred embodiment of the present invention, the camera 21 is first directed at a test target with the exposure time and gain of the camera set to the default values. When the camera is activated, the camera will detect an image, each pixel of which has a certain luminance value. The luminance value of each pixel is a particular numeric value between 0 and 255. The number of pixels at each luminance value is counted. The count values form a histogram such as that shown in Figure 3. Naturally in computer 22, the histogram is stored as data values. Figure 3 is merely an illustration of an example of such data.

1 The test target used in the first preferred embodiment is a standard photographer's "gray
2 card". That is, a card that has an image consisting of a gray background that is eighteen
3 percent gray.

4
5 Various mathematical parameters can be calculated from a histogram (or from the data
6 that can form a histogram). In first the preferred embodiment, the centroid value of the
7 luminance data is calculated and used for subsequent operations. However, it is noted
8 that in alternative embodiments, other values are used including:

- 9 a) The peak value of the histogram,
- 10 b) The root-mean-square value of the points that form the histogram,
- 11 c) The median value of the points that form the histogram.
- 12 d) The deviation value of the curve.
- 13 e) etc.

14
15 The value of a parameter from the histogram data (in the first preferred embodiment that
16 is the centroid value) is used as an index or pointer to values in a table which contains
17 exposure values. An example of such a table is given in Figure 3. Naturally it should be
18 understood that in computer 22, the data is stored as a conventional data table. Figure 4
19 is merely an illustration of such a table.

20
21 Figure 5 is a flow diagram illustrating the steps in the operation of the system shown in
22 Figure 2. First, as indicated by block 501, the control parameters of the camera are set to
23 a set of default values. In particular the exposure time is set to 1/90 second. Next as
24 indicated by block 502, the camera is pointed at a test target and an image is acquired.
25 The test target is a conventional photographers gray scale that is eighteen percent gray.

26
27 The luminance of the pixels in the image are measured (as indicated by block 503) and a
28 histogram of the luminance values is generated. In the particular embodiment, each pixel
29 has a luminance between 0 and 255 (i.e. an 8 bit representation) and the histogram has
30 an appearance somewhat like the histogram shown in Figure 3. Naturally, the actual
31 values will be dependent on various factors such as the amount of ambient light present.
32 Furthermore, if a 16 bit system were used, the luminance would have values between 0
33 and 65535.

1 Next (as indicated by block 504) the centroid of the histogram is calculated in a
2 conventional manner. That is, the centroid is calculated from the luminance data directly.
3 There is no need to actually construct or calculate the histogram. The histogram is merely
4 discussed herein to principles of the invention. A centroid is calculated directly from the
5 luminance data by adding together each luminance value times the number of pixels at
6 that value. For example: assume that there are:

7 3 pixels with value 1,
8 2 pixels with value 2
9 6 pixels with value 3
10 5 pixels with value 4
11 etc.

12 The centroid is then calculated as:

13 $(3 \times 1 + 2 \times 2 + 6 \times 3 + 5 \times 4 + \dots \text{etc.}) / (3 + 2 + 6 + 5 \dots \text{etc.})$

14 The value calculated for the centroid is used as an index or pointer to select a value in a
15 table such as the table shown in Figure 4 as indicated by block 506).

16

17 Next (block 506) the exposure time for the camera is set to the value obtained from the
18 table and an image is acquired using that exposure time (block 507). Finally (block 508)
19 a watermark is read from the acquired image in a conventional manner.

20

21 A flow diagram for a second preferred embodiment of the invention is shown in Figure 6.

22 In this alternative embodiment, no test target is used. Instead, the camera is pointed at
23 the image which contains a watermark and repeated frames containing the image are
24 acquired. Between each frame a new setting for the camera is calculated using
25 luminance values as previously described; however, in this embodiment, the luminance
26 values are the luminance values of an image that contains a watermark. After each
27 image is acquired an attempt is made to read the watermark, if the watermark can not be
28 read, the new camera setting are used to acquire another image. The process repeats
29 until the watermark can be read.

30

31 Figure 6 is a flow diagram of the operations. The camera is set to a relatively slow frame
32 rate (such as five frames per second) so that there is sufficient time between frames to
33 process the data to detect a watermark. This operation is conventional. The calculations

1 to determine a new setting for the camera take much less time than do the calculations to
2 detect a watermark.

3

4 The process begins as indicated by block 601 when the camera is pointed at an image
5 containing a watermark and an image is acquired. As indicated by blocks 602A and
6 602B, two operations proceed in parallel. First an attempt is made to read the watermark.
7 If that is successful (block 603) the operation goes to block 605 where the watermark data
8 is used for purposes such as those described in the previously referenced co-pending
9 applications. The second program that operates after each image is acquired in the
10 program indicated by block 602B. This program assembles data that forms a histogram of
11 the luminance of the pixels in the image, the centroid is calculated and a new exposure
12 value is obtained from a table (similar to the operation of the previous embodiment). Next
13 the camera is set to the new exposure value as indicated by block 604.

14

15 Finally if the watermark reading operation was not successful another image is acquired
16 and the process repeats.

17

18 The following is a more a specific description of a program that implements the operations
19 shown in Figure 6. This embodiment of the invention utilizes a commercially available
20 "3Com HomeConnect" PC Digital Camera. The camera as commercially available
21 provides a software interface, which allows many parameters to be queried and modified.
22 The available parameters and their value ranges shown in parenthesis are:

23

- 24 - Enable/disable the interface (e/d)
- 25 - Enable/disable Auto White Balance (AWB) tracking (e/d)
- 26 - Red balance (0-255)
- 27 - Blue balance (0-255)
- 28 - Color saturation (0-255)
- 29 - Set the mode of Auto Gain Control (AGC) operation (disabled, average mode,
30 average center window mode, peak mode)
- 31 - AGC bias (0-100)
- 32 - Shutter value (0-3900)
- 33 - Video gain (0-255)
- 34 - Gamma value (0-255)
- 35 - Image sharpness (0-255)

36

37 The only parameter that the program which implements the present invention changes
38 dynamically in its automatic operation is the shutter value. This value relates to a shutter

1 speed and has a non-linear range of 0-3900. In this scale, 0 is a shutter speed (or
2 exposure) of 1/31,500 of a second and 3900 is a shutter speed of 1/4 of a second.

3

4 When the program starts, the first thing it does is to enable the software interface to the
5 camera. The program saves the current values of all the camera parameters and then
6 puts in its own set of values. The camera's initial values will be restored when the
7 program shuts down. The following are initial values for various parameters that have
8 been found to operate satisfactorily in this particular embodiment of the invention.

9	-	AWB:	disabled
10	-	Red balance:	225
11	-	Blue balance:	128
12	-	Color saturation:	128
13	-	AGC:	disabled
14	-	Video gain:	128
15	-	Shutter:	174
16	-	Gamma:	100

17

18 When each image is acquired the program starts examining the video frame for
19 watermarks as indicated by block 602A. As each frame is received, its luminance centroid
20 is calculated and compared to our target luminance. The program dynamically adjusts the
21 shutter value in order to move the centroid towards the target luminance as indicated by
22 block 604.

23

24 Values used in the algorithm:

- 25 - Target luminance: 110 (range is 0-255)
- 26 - Distance is the distance between Centroid and Target
- 27 - Midpoint is one half of Distance
- 28 - Direction flag: set to 1 if Centroid < Target, otherwise set to -1
- 29 - LastShutter is the shutter value from the last frame we received
- 30 - Shutter is the current shutter value
- 31 - LastLuminance is the centroid for the last frame we received
- 32 - DeltaLuminance is the difference between LastLuminance and Centroid
- 33 - AdjustmentAmount is the change that we will be making to the Shutter value
34 for this frame
- 35 - LastAdjustment is the AdjustmentAmount we made on the last frame we
36 received
- 37 - Adjustment table (defined below)

38

39 The adjustment table lays out ranges of luminance values along with adjustment factors
40 and a scale flag. The adjustment factor is a multiplier which is used along with the
41 distance from Centroid to Midpoint. If the scale flag is set for a particular range then the
42 Current Shutter value is also factored into calculations involving that range.

	<u>Lower bound</u>	<u>Upper bound</u>	<u>Factor</u>	<u>Flag</u>
1				
2				
3	0	29	7.5	Off
4	30	69	0.75	On
5	70	94	0.95	On
6	95	104	0.75	On
7	105	115	0.5	On
8	116	135	0.5	On
9	136	150	0.7	On
10	151	225	1.5	On
11	226	255	2.0	Off

12

13 The following algorithm is implemented by the program:

14

15 If Centroid has not changed since the last frame and the distance from Centroid to
 16 Target < 20 then don't make any adjustments

17

18 Set CurrentAdjustment to 0

19

20 Walk through the Adjustment Table. For each entry in the table, if any part of the

21 Area, defined as the area between Centroid and

22 Midpoint falls within the range of Lower Bound to Upper Bound then calculate

23 Scale and AdjustmentIncrement as follows:

24

25 If Flag is Off then

26 Scale = Factor

27 Else

28 Scale = Factor * Log (Current Shutter)

29

30 AdjustmentIncrement = (amount of Area that falls between Lower Bound
 31 and Upper Bound) * Scale * Direction

32

33 Each AdjustmentIncrement is added to CurrentAdjustment.

34

35

36 Compare DeltaLuminance to LastAdjustment. If DeltaLuminance is a positive

37 number while LastAdjustment is negative or vice-versa then it means that

38 movement of Centroid is going in the opposite direction from our adjustments. We

39 will continue to adjust until Centroid movement switches directions, then we will

40 slow down and wait for Centroid to catch up. At the same time we will limit

41 CurrentAdjustment changes to be no more than 25% of the Shutter value.

42

43 AdjustmentPercentage = Abs(CurrentAdjustment / Shutter)

```
1         If AdjustmentPercentage > 25%
2             CurrentAdjustment = Shutter * 25% * Direction
3
4     Else
5
6         CentroidRate = Abs( DeltaLuminance / LastLuminance )
7
8         If LastAdjustment was non-zero and CurrentAdjustment is non-zero
9
10            ShutterRate = Abs( LastAdjustment / LastShutter )
11            AdjustmentRatio = Abs( CurrentAdjustment / LastAdjustment )
12
13            If ShutterRate > CentroidRate and ShutterRate < AdjustmentRatio
14
15                AdjustmentPercentage = Abs( CurrentAdjustment / Shutter )
16                MaxPercentage = ( Target - Distance ) / Target
17
18                If AdjustmentPercentage > MaxPercentage
19
20                    CurrentAdjustment = Shutter * MaxPercentage *
21                Direction
22
23                Else
24
25                    TestAdjustment = CurrentAdjustment * 3 *
26                CentroidRate / ShutterRate
27
28                    If TestAdjustment < CurrentAdjustment
29
30                        CurrentAdjustment = TestAdjustment
31
32
33                Check to make sure that CurrentAdjustment will not push Shutter below 0. If so
34                then
35
36                    CurrentAdjustment = Shutter * 2/3 * Direction
37
38
39                Make the change then update our values:
40
41                Shutter = Shutter + CurrentAdjustment
42
43                LastShutter = Shutter
44                LastCentroid = Centroid
45                LastAdjustment = CurrentAdjustment
46
47
48
```

1 It is noted that in the preferred embodiments described above, the invention is used to
2 only set the exposure time of the camera. In other embodiments, the table shown in
3 Figure 4 is expanded to also include the value of the gain and the gain of the camera is
4 set utilizing the present invention. In such an embodiment both exposure time and gain
5 can be set using one parameter from the histogram data. Various rules could be used to
6 construct the table used to obtain values of the exposure time and gain, that is, to map the
7 one dimensional parameter value into a two dimensional exposure/gain value. In similar
8 fashion other parameters of the camera can be set utilizing the present invention.

9
10 While the invention has been described with respect to preferred embodiments thereof, it
11 should be understood that various other changes in form and detail are possible without
12 departing from the spirit and scope of the invention. For example, while the invention is
13 particularly illustrated with reference to a camera employing a CCD detector, any other
14 optical sensor technology can likewise be employed. Similarly, while the invention is
15 particularly described with reference to a video camera, the same principles are equally
16 applicable to watermark detection with non-video image acquisition device. Yet further,
17 while a table was used in the illustrated embodiment to generate camera settings, other
18 known structures and approaches (e.g., formulas) using the same or similar input
19 information can be readily substituted. Still further, while a histogram was described as a
20 preferred analysis technique, other statistical analyses for characterizing the camera's
21 response can similarly be utilized. Accordingly, the scope of applicant's invention is
22 limited only by the structure and methods described in the appended claims and
23 equivalents thereto.

24

25 I claim:

11

- 1 1) The method of adjusting the control setting of an electronic camera which comprises:
2 adjusting said control setting to a default value,
3 acquiring a first image with the camera,
4 the luminance values of the pixels in said first image forming a histogram,
5 calculating the value of at least one parameter of said histogram.
6 using said value to obtain a second value for said control setting,
7 adjusting said camera in accordance with said second value,
8 acquiring at least one additional image with said control setting set to said second value.
9
- 10 2) The method claimed in claim 1 including the step of reading a digital watermark from
11 said additional image.
12
- 13 3) The method claimed in claim 1 wherein said parameter is the centroid of said
14 histogram.
15
- 16 4) The method claimed in claim 3 including the step of reading a digital watermark from
17 said additional image.
18
- 19 5) The method in claim 1 wherein said parameter is the peak value of said centroid.
20
- 21 6) The method in claim 1 wherein said control setting is the exposure time of said camera.
22
- 23 7) The method in claim 1 wherein the first image acquired by said camera is an image of a
24 photographer's gray card.
25
- 26 8) The method in claim 1 wherein said parameter is the variance of said histogram.
27
- 28 9) The method in claim 1 wherein control setting includes the gain of said camera.
29
- 30 10) An electronic camera which has at least one control which can be adjusted:
31 means for adjusting said control setting to a default value,
32 means for acquiring a first image with the camera,
33 the luminance values of the pixels in said first image forming a histogram,
34 means for calculating the value of at least one parameter of said histogram,

12

- 1 means for using said value to obtain a second value for said control setting,
2 means for adjusting said camera in accordance with said second value,
3 means for acquiring at least one additional image with said control setting set to said
4 second value.
- 5
- 6 11) An electronic camera which has at least one control which can be adjusted:
7 a computer which controls said camera,
8 a program for controlling said computer to facilitate,
9 adjusting said control to a default value,
10 acquiring a first image with the camera with said control adjusted to said default value,
11 the luminance values of the pixels in said first image forming a histogram,
12 calculating the value of at least one parameter of said histogram,
13 using said value to obtain a second value for said control setting,
14 adjusting the control of said camera in accordance with said second value,
15 acquiring at least one additional image with said control setting set to said second value,
16 detecting a watermark in said additional image.
- 17
- 18 12) The camera recited in claim 11 wherein said parameter is the centroid of said
19 histogram.
- 20
- 21 13) The camera recited in claim 11 wherein said parameter is the peak value in said
22 histogram.
- 23
- 24 14) The camera recited in claim 11 wherein said control is the exposure time of said
25 camera.
- 26
- 27 15) The method recited in claim 1 wherein said first image is an image of a
28 photographer's gray card.
- 29
- 30 16) The method recited in claim 1 wherein said default setting is an exposure time of
31 1/90 second.

1

2 17) The method of adjusting the control setting of an electronic camera which comprises:

3 acquiring a first image with the camera,

4 the luminance values of the pixels in said first image forming a histogram,

5 calculating the value of at least one parameter of said histogram,

6 using said value to obtain a new value for said control setting,

7 adjusting said camera in accordance with said new value,

8 attempting to read a watermark in said first image, and

9 if said read operation is not successful, repeating said process.

10

11 18) The method recited in claim 17 wherein said parameter is the centroid of said

12 histogram.

13

14 19) The method recited in claim 17 wherein said control setting is the exposure time of

15 said camera.

16

1/4

Configuration Profile Options			LESS...	
<div>SAVE</div> <div>LOAD</div> <div>DEFAULTS</div>			<div>Timed Profiles</div>	
<div>Quality vs. Frame Rate</div> <div>High Quality</div>			<div>Image Sharpness</div> <div>50%</div>	
<div>Shutter Speed Control</div> <div>1/ 55 th Second</div>			<div>Automatic Gain Mode</div> <div>AGC Off</div>	
<div>Back Light Compensation</div> <div>0%</div>			<div>Brightness Control</div> <div>50%</div>	
<div>Gamma</div> <div>2.01</div>			<div>Manual Gain Control</div> <div>0%</div>	
<div><input type="checkbox"/> LED <input checked="" type="checkbox"/> 60 Hz</div> <div><input type="checkbox"/> Freeze <input type="checkbox"/> Negative</div> <div><input type="checkbox"/> Mirror <input type="checkbox"/> Flip</div>			<div><input type="checkbox"/> Auto WB Tracking</div> <div>Manual White Balance</div>	
<div>HELP</div> <div>ABOUT</div>			<div>Color Level</div> <div>50%</div>	
<div> OK</div> <div> Cancel</div>			<div>Red Balance</div> <div>92%</div>	
			<div>Blue Balance</div> <div>50%</div>	

FIG. 1

2/4




FIG. 2




FIG. 3

FIG. 4

[illegible]

3/4




FIG. 5

4/4




FIG. 6

INTERNATIONAL SEARCH REPORT

International application No.

PCT/US00/32013

A. CLASSIFICATION OF SUBJECT MATTER

IPC(7) :G06K 9/00

US CL :382/100: 348/175, 229, 349, 364

According to International Patent Classification (IPC) or to both national classification and IPC

B. FIELDS SEARCHED

Minimum documentation searched (classification system followed by classification symbols)

U.S. : 382/100: 348/175, 229, 349, 364

Documentation searched other than minimum documentation to the extent that such documents are included in the fields searched

Electronic data base consulted during the international search (name of data base and, where practicable, search terms used)

EAST

C. DOCUMENTS CONSIDERED TO BE RELEVANT

Category*	Citation of document, with indication, where appropriate, of the relevant passages	Relevant to claim No.
X	US 5,572,433 A (FALCONER et al) 05 November 1996, col. 6, lines 31-67.	1-2, 5-11, 14-17, 19
A, E	US 6,177,956 A (ANDERSON et al) 23 January 2001, col. 2, lines 15-30.	1-19

☐ Further documents are listed in the continuation of Box C.
 ☐ See patent family annex.

* Special categories of cited documents:	*T* later document published after the international filing date or priority date and not in conflict with the application but cited to understand the principle or theory underlying the invention
A document defining the general state of the art which is not considered to be of particular relevance	*X* document of particular relevance; the claimed invention cannot be considered novel or cannot be considered to involve an inventive step when the document is taken alone
E earlier document published on or after the international filing date	*Y* document of particular relevance; the claimed invention cannot be considered to involve an inventive step when the document is combined with one or more other such documents, such combination being obvious to a person skilled in the art
L document which may throw doubts on priority claim(s) or which is cited to establish the publication date of another citation or other special reason (as specified)	*G* document member of the same patent family
O document referring to an oral disclosure, use, exhibition or other means	
P document published prior to the international filing date but later than the priority date claimed	

Date of the actual completion of the international search

30 JANUARY 2001

Date of mailing of the international search report

23 MAR 2001

 Name and mailing address of the ISA/US
 Commissioner of Patents and Trademarks
 Box PCT
 Washington, D.C. 20231

Facsimile No. (703) 305-3230

Authorized officer

MATTHEW C. BELLA

Telephone No. (703) 308-6829